

RL78/G23

HS300x Sample sketch (Arduino™ sketch)

Introduction

This application note describes how to use the RL78/G23-64p Fast Prototyping Board (FPB) library for Arduino to display data from the HS3001 sensor on the serial monitor of the Arduino™ IDE.

Target Device

Evaluation board : RL78/G23-64p Fast Prototyping Board

Sensor evaluation board : US082-HS3001EVZ

Trademarks

Arduino is a trademark of Arduino SA.

Contents

1. System overview	3
2. Operation confirmation environment	4
3. Build development environment.....	5
3.1 Board connection.....	5
3.2 List of pins used.....	6
3.3 Setup of Arduino™ IDE	7
4. Software	10
4.1 Overview of sample code	10
4.2 API functions	11
4.2.1 HS300x module.....	11
4.2.2 Other APIs	13
4.3 Operating procedure of sample sketch	14
4.4 Flowchart	18
5. Notes	19
5.1 COM port is not displayed on the Windows Device Manager	19
5.2 Program is not written correctly to RL78/G23-64p Fast Prototyping Board	20
6. Sample Code.....	21
7. Reference Documnets	21
Revision History	22

1. System overview

This system is composed of the RL78/G23-64p Fast Prototyping Board (RL78/G23-64p FPB) and the US082-HS3001EVZ with the humidity and temperature HS3001. Arduino™ IDE is used for creating a program and writing a program to RL78/G23. The data from the HS3001 is displayed on the serial monitor.

The block configuration of the sample code used in this system is shown below.




Figure 1-1 Block configuration of software

The simple diagram of this system configuration is shown below.




Figure 1-2 System configuration

2. Operation confirmation environment

The operation of the sample code provided by this application note has been tested under the following conditions.

Table 2-1 Operation confirmation environments (Hardware)

Item	Description
Evaluation board	RL78/G23-64p Fast Prototyping Board – RTK7RLG230CLG000BJ
Sensor evaluation board	US082-HS3001EVZ
Operating Voltage	5V

Table 2-2 Operation confirmation environments (Software)

Item	Description	Version
OS	Windows 10	-
Integrated development environment	Arduino™ IDE	2.0.4
Library	RL78/G23-64p FPB library for Arduino	2.0.0

3. Build development environment

How to connect boards and how to set up the Arduino™ IDE are explained.

The Arduino™ IDE 2.0.4 is used in this system. Installation of the Arduino™ IDE 2.0.4 or later is necessary if it is not installed.

3.1 Board connection

The PC and the RL78/G23-64p FPB are connected via USB as shown in Figure 3-1. The RL78/G23-64p FPB and the US082-HS3001EVZ are connected via jumper wires.

USB is used for power supply to the RL78/G23-64p FPB in this system. For the power supply, check the circuit of the RL78/G23-64p FPB by referring to the manual, and set jumpers if required.

In this system, jumpers of the RL78/G23-64p FPB are set as shown in Table 3-1.

Table 3-1 Jumper pins setting of RL78/G23-64p FPB

Jumper pin	Setting	Function
J8	1-2 short-circuit	COM port debugging
J9		
J11		
J13	Open-circuit	
J17	1-2 short-circuit	5-V power supply




Figure 3-1 Connection of boards

3.2 List of pins used

The pins used in this system are shown below.

Table 3-2 Pins used

Item	Arduino™ signal name	Pin number of MCU	Pin
I2C	SDA	18	SDAA0/P61
	SCL	17	SCLA0/P60
VDD	5V	-	-
GND	GND	14	-

For detailed pin descriptions of each board, refer to the following manuals.

- RL78/G23-64p Fast Prototyping Board User's Manual (R20UT4814)
- US082-HS3001EVZ Evaluation Board Manual (R36UZ0004)

3.3 Setup of Arduino™ IDE

The setup procedure of Arduino™ IDE is explained.

Remark. The setup procedure is almost the same as the procedure explained on the [Quick Start Guide : renesas/Arduino Wiki · GitHub](#). The sample sketch to flash LED is described on the above site. Refer to it if required.

1. Start the Arduino™ IDE.
2. Click the [Tools] - [Board] - [Boards Manager...] menu.




Figure 3-2 Selection of [Boards Manager...]

3. Specify “All” at the [Type] and input “RL78” in the textbox. Then, “RL78/G23-64p Fast Prototyping Board” is displayed. Next, click the [INSTALL]. Version 2.0.0 is used in this sample code.




Figure 3-3 Installation of Board Manager

- Select the serial port assigned to the RL78/G23-64p FPB from the [Tools] - [Port] menu.
COM port number can be checked at the Device Manager of Windows.




Figure 3-4 Selection of serial port

- Select the [Tools] - [Board] - [RL78/G23-64p Fast Prototyping Board] - [RL78/G23-64p Fast Prototyping Board] menu.




Figure 3-5 Selection of board

4. Software

4.1 Overview of sample code

This sample code gets the data from the HS300x and calculate them to change to the value of temperature and humidity.

This sample code is composed of the sample sketch for the Arduino™ IDE and the HS300x module (API for Arduino). The file structure is shown below.

For details of the HS300x module, refer to the “4.2.1 HS300x module”, for details of the sample sketch, refer to the “4.3 Operating procedure of sample sketch”.




Figure 4-1 File structure of sample code

4.2 API functions

4.2.1 HS300x module

The list of APIs contained in the HS300x module is shown below.

Table 4-1 API list of HS300x module

API function name	Function
int begin()	Measurement preparation <ul style="list-style-type: none"> • Call the initialization function of Wire channel. • Call the <code>_measurementReq</code> function.
float readTemperature()	Return the value of temperature.
float readHumidity()	Return the value of humidity.
uint8_t _readSensor()	Get the data from HS300x sensor.
int8_t _measurementReq()	Request for measurement <ul style="list-style-type: none"> • Prepare for IIC transition. • Call the <code>_readSensor</code> function.

The specification of HS300x module's API functions is shown below.

int begin()

Outline	Call the function of the Wire library to initialize the Wire channel and call the <code>_measurementReq</code> function of the HS300x module in preparation for the measurement.	
Argument	None	
Return value	Description	Readout result from sensor
	Return value	0x01: Normal end (success) 0x00: Failed of read 0xFF: The read data is an abnormal value.
	Data type	uint8_t

float readTemperature()

Outline	Return the value of the temperature if the return value of the <code>_measurementReq</code> function is the normal end. Return the "NAN" except the normal end.	
Argument	None	
Return value	Description	The value of temperature or the "NAN" indicating except the normal end
	Return value	The value of temperature NAN
	Data type	float

float readHumidity()

Outline	Return the value of the humidity if the return value of the <code>_measurementReq</code> function is the normal end. Return the "NAN" except the normal end.	
Argument	None	
Return value	Description	The value of humidity or the "NAN" indicating except the normal end
	Return value	The data of humidity NAN
	Data type	float

Remark. NAN : NaN (Not a Number)

uint8_t _readSensor()

Outline	Get the data from HS300x sensor and calculate the value of temperature and humidity from the raw data.	
Argument	None	
Return value	Description	Readout result from sensor
	Return value	0x01: Normal end (success) 0x00: Failed of read 0xFF: The read data is an abnormal value.
	Data type	uint8_t

int8_t _measurementReq()

Outline	To request for the measurement, call the beginTransmission function, the write function, the endTransmission function of the Wire library and the _readSensor function of the HS300x module.	
Argument	None	
Return value	Description	Readout result from sensor
	Return value	0x01: Normal end (success) 0x00: Failed of read 0xFF: The read data is an abnormal value.
	Data type	uint8_t

4.2.2 Other APIs

This sample code uses the Wire library for I2C communication and the HardwareSerial (Serial) library in addition to the HS300x module.

Table 4-2 List of APIs other than HS300x module

API function	Function
Wire.begin(address)	Initialize the Wire library. In this sample code, connect to the I2C bus as the master.
Wire.beginTransmission(address)	Prepare for sending to the communication partner.
Wire.endTransmission()	Send the sequence to the communication partner to start the I2C communication.
Wire.requestFrom(address, count)	Send the sequence to the communication partner to read the data.
Wire.write(value)	Append the data to the end of the transmit buffer.
Wire.read()	Get 1-byte data from the receive buffer.
Serial.begin(speed)	Specify the data transfer speed (bps) of serial communication.
Serial.print(data, format)	Output the data to the serial port.
Serial.println(data, format)	Line feed for each data and output to the serial port.

For API function specifications of each library, refer to the website of Arduino™ and the other.

[API List · renesas/Arduino Wiki · GitHub](#)

[Wire - Arduino Reference](#)

[Serial - Arduino Reference](#)

4.3 Operating procedure of sample sketch

The operation procedure of this sample sketch is shown below. Before the steps below, setup the Arduino™ IDE in the “3.3 Setup of Arduino™ IDE”.

1. Click the [Sketch] - [Include Library] - [Add .ZIP Library...] menu of the Arduino™ IDE. Then, specify the sample code zip file (HS300x.zip) and click the [Open].




Figure 4-2 Include HS300x module

2. Select the [File] - [Examples] - [HS300x] - [ReadSensors] menu to open the sample sketch "ReadSensors.ino".




Figure 4-3 Select sample sketch

3. Click the [Verify] icon to start compiling the sketch.




Figure 4-4 Compile sketch

4. After compiling is finished, click the [Upload] icon to write the program to the device.




Figure 4-5 Write sketch

- 5. After writing, click the [Serial Monitor] icon to open the serial monitor. Temperature and Humidity are displayed on the serial monitor every second.




Figure 4-6 Serial monitor of Arduino™ IDE

4.4 Flowchart

The flow of the sample sketch is shown below.




Figure 4-7 Flowchart of sample sketch

5. Notes

5.1 COM port is not displayed on the Windows Device Manager

When connecting the PC and the evaluation board (RL78/G23-64p FPB) for the first time, the PC may not recognize the port and the COM port may not be displayed in Windows Device Manager.

If the COM port is not displayed, install the driver of the USB-to-serial convertor (FT232RQ) from FTDI on the RL78/G23-64p FPB by the following procedure.

1. Download the latest driver installer for the target OS from FTDI's website and install it.
<https://ftdichip.com/drivers/vcp-drivers/>
2. After installation, "USB Serial Port (COMx)" is displayed under the "Ports (COM & LPT)" on the Device Manager. In the following figure, COM5 is the target COM port.




Figure 5-1 Windows Device Manager after installation of device driver

For details of USB-to-serial convertor and COM port, refer to "5.11 USB-to-Serial Converter" and "5.12 USB-to-Serial Converter Reset Header" in RL78/G23-64p Fast Prototyping Board User's manual.

5.2 Program is not written correctly to RL78/G23-64p Fast Prototyping Board

It may not be connected correctly the PC and the RL78/G23-64p FPB even if “USB Serial Port (COMx)” is displayed. Because the RL78/G23-64p FPB is not recognized correctly.

If the program is not written correctly, double-click the target COM port on Windows Device Manager and clear the checkbox of [Serial Emulator].




Figure 5-2 Setting example of target COM

6. Sample Code

There is the sample code for this application note.

Sample code can be downloaded from the Renesas Electronics website.

7. Reference Documents

RL78/G23 User's Manual: Hardware (R01UH0896)

RL78/G23-64p Fast Prototyping Board User's Manual (R20UT4814)

HS300x Datasheet (R36DS0010)

US082-HS3001EVZ Evaluation Board Manual (R36UZ0004)

The latest versions can be downloaded from the Renesas Electronics website.

Technical update

The latest versions can be downloaded from the Renesas Electronics website.

All trademarks and registered trademarks are the property of their respective owners.

Revision History

Rev.	Date	Description	
		Page	Summary
1.00	April. 21, 2023	-	First Edition

General Precautions in the Handling of Microprocessing Unit and Microcontroller Unit Products

The following usage notes are applicable to all Microprocessing unit and Microcontroller unit products from Renesas. For detailed usage notes on the products covered by this document, refer to the relevant sections of the document as well as any technical updates that have been issued for the products.

1. Precaution against Electrostatic Discharge (ESD)

A strong electrical field, when exposed to a CMOS device, can cause destruction of the gate oxide and ultimately degrade the device operation. Steps must be taken to stop the generation of static electricity as much as possible, and quickly dissipate it when it occurs. Environmental control must be adequate. When it is dry, a humidifier should be used. This is recommended to avoid using insulators that can easily build up static electricity.

Semiconductor devices must be stored and transported in an anti-static container, static shielding bag or conductive material. All test and measurement tools including work benches and floors must be grounded. The operator must also be grounded using a wrist strap. Semiconductor devices must not be touched with bare hands. Similar precautions must be taken for printed circuit boards with mounted semiconductor devices.

2. Processing at power-on

The state of the product is undefined at the time when power is supplied. The states of internal circuits in the LSI are indeterminate and the states of register settings and pins are undefined at the time when power is supplied. In a finished product where the reset signal is applied to the external reset pin, the states of pins are not guaranteed from the time when power is supplied until the reset process is completed. In a similar way, the states of pins in a product that is reset by an on-chip power-on reset function are not guaranteed from the time when power is supplied until the power reaches the level at which resetting is specified.

3. Input of signal during power-off state

Do not input signals or an I/O pull-up power supply while the device is powered off. The current injection that results from input of such a signal or I/O pull-up power supply may cause malfunction and the abnormal current that passes in the device at this time may cause degradation of internal elements. Follow the guideline for input signal during power-off state as described in your product documentation.

4. Handling of unused pins

Handle unused pins in accordance with the directions given under handling of unused pins in the manual. The input pins of CMOS products are generally in the high-impedance state. In operation with an unused pin in the open-circuit state, extra electromagnetic noise is induced in the vicinity of the LSI, an associated shoot-through current flows internally, and malfunctions occur due to the false recognition of the pin state as an input signal become possible.

5. Clock signals

After applying a reset, only release the reset line after the operating clock signal becomes stable. When switching the clock signal during program execution, wait until the target clock signal is stabilized. When the clock signal is generated with an external resonator or from an external oscillator during a reset, ensure that the reset line is only released after full stabilization of the clock signal. Additionally, when switching to a clock signal produced with an external resonator or by an external oscillator while program execution is in progress, wait until the target clock signal is stable.

6. Voltage application waveform at input pin

Waveform distortion due to input noise or a reflected wave may cause malfunction. If the input of the CMOS device stays in the area between V_{IL} (Max.) and V_{IH} (Min.) due to noise, for example, the device may malfunction. Take care to prevent chattering noise from entering the device when the input level is fixed, and also in the transition period when the input level passes through the area between V_{IL} (Max.) and V_{IH} (Min.).

7. Prohibition of access to reserved addresses

Access to reserved addresses is prohibited. The reserved addresses are provided for possible future expansion of functions. Do not access these addresses as the correct operation of the LSI is not guaranteed.

8. Differences between products

Before changing from one product to another, for example to a product with a different part number, confirm that the change will not lead to problems. The characteristics of a microprocessing unit or microcontroller unit products in the same group but having a different part number might differ in terms of internal memory capacity, layout pattern, and other factors, which can affect the ranges of electrical characteristics, such as characteristic values, operating margins, immunity to noise, and amount of radiated noise. When changing to a product with a different part number, implement a system-evaluation test for the given product.

Notice

1. Descriptions of circuits, software and other related information in this document are provided only to illustrate the operation of semiconductor products and application examples. You are fully responsible for the incorporation or any other use of the circuits, software, and information in the design of your product or system. Renesas Electronics disclaims any and all liability for any losses and damages incurred by you or third parties arising from the use of these circuits, software, or information.
2. Renesas Electronics hereby expressly disclaims any warranties against and liability for infringement or any other claims involving patents, copyrights, or other intellectual property rights of third parties, by or arising from the use of Renesas Electronics products or technical information described in this document, including but not limited to, the product data, drawings, charts, programs, algorithms, and application examples.
3. No license, express, implied or otherwise, is granted hereby under any patents, copyrights or other intellectual property rights of Renesas Electronics or others.
4. You shall be responsible for determining what licenses are required from any third parties, and obtaining such licenses for the lawful import, export, manufacture, sales, utilization, distribution or other disposal of any products incorporating Renesas Electronics products, if required.
5. You shall not alter, modify, copy, or reverse engineer any Renesas Electronics product, whether in whole or in part. Renesas Electronics disclaims any and all liability for any losses or damages incurred by you or third parties arising from such alteration, modification, copying or reverse engineering.
6. Renesas Electronics products are classified according to the following two quality grades: "Standard" and "High Quality". The intended applications for each Renesas Electronics product depends on the product's quality grade, as indicated below.
 - "Standard": Computers; office equipment; communications equipment; test and measurement equipment; audio and visual equipment; home electronic appliances; machine tools; personal electronic equipment; industrial robots; etc.
 - "High Quality": Transportation equipment (automobiles, trains, ships, etc.); traffic control (traffic lights); large-scale communication equipment; key financial terminal systems; safety control equipment; etc.Unless expressly designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not intended or authorized for use in products or systems that may pose a direct threat to human life or bodily injury (artificial life support devices or systems; surgical implantations; etc.), or may cause serious property damage (space system; undersea repeaters; nuclear power control systems; aircraft control systems; key plant systems; military equipment; etc.). Renesas Electronics disclaims any and all liability for any damages or losses incurred by you or any third parties arising from the use of any Renesas Electronics product that is inconsistent with any Renesas Electronics data sheet, user's manual or other Renesas Electronics document.
7. No semiconductor product is absolutely secure. Notwithstanding any security measures or features that may be implemented in Renesas Electronics hardware or software products, Renesas Electronics shall have absolutely no liability arising out of any vulnerability or security breach, including but not limited to any unauthorized access to or use of a Renesas Electronics product or a system that uses a Renesas Electronics product. RENESAS ELECTRONICS DOES NOT WARRANT OR GUARANTEE THAT RENESAS ELECTRONICS PRODUCTS, OR ANY SYSTEMS CREATED USING RENESAS ELECTRONICS PRODUCTS WILL BE INVULNERABLE OR FREE FROM CORRUPTION, ATTACK, VIRUSES, INTERFERENCE, HACKING, DATA LOSS OR THEFT, OR OTHER SECURITY INTRUSION ("Vulnerability Issues"). RENESAS ELECTRONICS DISCLAIMS ANY AND ALL RESPONSIBILITY OR LIABILITY ARISING FROM OR RELATED TO ANY VULNERABILITY ISSUES. FURTHERMORE, TO THE EXTENT PERMITTED BY APPLICABLE LAW, RENESAS ELECTRONICS DISCLAIMS ANY AND ALL WARRANTIES, EXPRESS OR IMPLIED, WITH RESPECT TO THIS DOCUMENT AND ANY RELATED OR ACCOMPANYING SOFTWARE OR HARDWARE, INCLUDING BUT NOT LIMITED TO THE IMPLIED WARRANTIES OF MERCHANTABILITY, OR FITNESS FOR A PARTICULAR PURPOSE.
8. When using Renesas Electronics products, refer to the latest product information (data sheets, user's manuals, application notes, "General Notes for Handling and Using Semiconductor Devices" in the reliability handbook, etc.), and ensure that usage conditions are within the ranges specified by Renesas Electronics with respect to maximum ratings, operating power supply voltage range, heat dissipation characteristics, installation, etc. Renesas Electronics disclaims any and all liability for any malfunctions, failure or accident arising out of the use of Renesas Electronics products outside of such specified ranges.
9. Although Renesas Electronics endeavors to improve the quality and reliability of Renesas Electronics products, semiconductor products have specific characteristics, such as the occurrence of failure at a certain rate and malfunctions under certain use conditions. Unless designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not subject to radiation resistance design. You are responsible for implementing safety measures to guard against the possibility of bodily injury, injury or damage caused by fire, and/or danger to the public in the event of a failure or malfunction of Renesas Electronics products, such as safety design for hardware and software, including but not limited to redundancy, fire control and malfunction prevention, appropriate treatment for aging degradation or any other appropriate measures. Because the evaluation of microcomputer software alone is very difficult and impractical, you are responsible for evaluating the safety of the final products or systems manufactured by you.
10. Please contact a Renesas Electronics sales office for details as to environmental matters such as the environmental compatibility of each Renesas Electronics product. You are responsible for carefully and sufficiently investigating applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive, and using Renesas Electronics products in compliance with all these applicable laws and regulations. Renesas Electronics disclaims any and all liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations.
11. Renesas Electronics products and technologies shall not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any applicable domestic or foreign laws or regulations. You shall comply with any applicable export control laws and regulations promulgated and administered by the governments of any countries asserting jurisdiction over the parties or transactions.
12. It is the responsibility of the buyer or distributor of Renesas Electronics products, or any other party who distributes, disposes of, or otherwise sells or transfers the product to a third party, to notify such third party in advance of the contents and conditions set forth in this document.
13. This document shall not be reprinted, reproduced or duplicated in any form, in whole or in part, without prior written consent of Renesas Electronics.
14. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products.

(Note1) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its directly or indirectly controlled subsidiaries.

(Note2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics.

(Rev.5.0-1 October 2020)

Corporate Headquarters

TOYOSU FORESIA, 3-2-24 Toyosu,
Koto-ku, Tokyo 135-0061, Japan
www.renesas.com

Trademarks

Renesas and the Renesas logo are trademarks of Renesas Electronics Corporation. All trademarks and registered trademarks are the property of their respective owners.

Contact information

For further information on a product, technology, the most up-to-date version of a document, or your nearest sales office, please visit:
www.renesas.com/contact/.