

[Notes]

R20TS0477ES0100  
Rev.1.00  
Sep. 16, 2019

e<sup>2</sup> studio Smart Configurator Plug-in,  
Smart Configurator for RX

Outline

When using the e<sup>2</sup> studio Smart Configurator Plug-in and Smart Configurator for RX, note the following point.

1. When using the automatic adjustment function for time error adjustment on the Realtime Clock

1. When Using the Automatic Adjustment Function for Time Error Adjustment on the Realtime Clock

1.1 Applicable Products

- e<sup>2</sup> studio V7.0.0 (Smart Configurator Plug-in V1.4.0) or later
- Smart Configurator for RX V1.4.0 or later

1.2 Applicable Devices

- RX family:  
RX110, RX111, RX113, RX130, RX230, RX231, RX23W,  
RX64M, RX651, and RX65N groups

1.3 Details

When the automatic adjustment function for timer error adjustment is used on the Realtime Clock, the order of code initialization for the PMADJ register and AADJE/AADJP bits in RCR2 register is inverted, which may affect the automatic adjustment accuracy.

Error location

```

*****/
/* Start user code for global. Do not edit comment generated here */
/* End user code. Do not edit comment generated here */

/*****
* Function Name: R_Config_RTC_Create
* Description   : This function initializes the RTC module
* Arguments    : None
* Return Value : None
*****/

void R_Config_RTC_Create(void)
{
    uint16_t w_count;
    uint32_t rw_count;
    volatile uint32_t dummy;
    ...

    /* Set clock error adjustment values */
    RTC.RADJ.BYTE = _40_RTC_TIMER_ERROR_ADJUST_PLUS | _03_RTC_AUTO_ADJUSTMENT_VALUE;
    while (( _40_RTC_TIMER_ERROR_ADJUST_PLUS | _03_RTC_AUTO_ADJUSTMENT_VALUE) != RTC.RADJ.BYTE)
    {
        /* Wait for this write to complete. */
    }

    RTC.RCR2.BYTE |= ( _10_RTC_AUTO_ADJUSTMENT_ENABLE | _20_RTC_AUTO_ADJUSTMENT_PERIOD_8SEC);
    ...
}

```

The diagram highlights two code blocks with red boxes. The first block contains the initialization of RTC.RADJ.BYTE and a while loop that waits for the write to complete. The second block contains the initialization of RTC.RCR2.BYTE. A blue arrow points from the first block to the second, and another blue arrow points from the second block back to the first, indicating that the order of execution is inverted. A red text box at the bottom states: "The initialize sequence for these 2 sets of codes is inverted".

### 1.4 Conditions

The error occurs when Realtime clock component is added in Smart Configurator and the automatic adjustment function for timer error adjustment is used ('Enable automatic adjustment' check box is checked).



### 1.5 Workaround

Change the order of code initialization for setting the PMADJ register and AADJE/AADJP bits in RCR2 register in the source file below.

Note: When code is generated again, generated code returns to the state before correction. Therefore, correct the source file each time you generate code.

- Source file: "<RTC-configuration-name>.c"
- Function: "void r\_<RTC- configuration-name>\_Create (void)"

The <RTC- configuration-name> varies depending on the selected component of RTC.

Below is an example of modification when the <RTC-configuration-name> is Config\_RTC (initial value) for RX64M.

#### Before correction

```

*****/
/* Start user code for global. Do not edit comment generated here */
/* End user code. Do not edit comment generated here */

/*****
* Function Name: R_Config_RTC_Create
* Description  : This function initializes the RTC module
* Arguments   : None
* Return Value: None
*****/

void R_Config_RTC_Create(void)
{
    uint16_t w_count;
    uint32_t rw_count;
    volatile uint32_t dummy;
    ...

    /* Set clock error adjustment values */
    RTC.RADJ.BYTE = _40_RTC_TIMER_ERROR_ADJUST_PLUS | _03_RTC_AUTO_ADJUSTMENT_VALUE;
    while (( _40_RTC_TIMER_ERROR_ADJUST_PLUS | _03_RTC_AUTO_ADJUSTMENT_VALUE) != RTC.RADJ.BYTE)
    {
        /* Wait for this write to complete. */
    }

    RTC.RCR2.BYTE |= ( _10_RTC_AUTO_ADJUSTMENT_ENABLE | _20_RTC_AUTO_ADJUSTMENT_PERIOD_8SEC );
    ...
}

```

Change the order of these 2 set of codes

## After correction

```

*****
/* Start user code for global. Do not edit comment generated here */
/* End user code. Do not edit comment generated here */

/*****
* Function Name: R_Config_RTC_Create
* Description  : This function initializes the RTC module
* Arguments   : None
* Return Value: None
*****/

void R_Config_RTC_Create(void)
{
    uint16_t w_count;
    uint32_t rw_count;
    volatile uint32_t dummy;
    ...

    RTC.RCR2.BYTE |= ( _10_RTC_AUTO_ADJUSTMENT_ENABLE | _20_RTC_AUTO_ADJUSTMENT_PERIOD_8SEC);

    /* Set clock error adjustment values */
    RTC.RADJ.BYTE = _40_RTC_TIMER_ERROR_ADJUST_PLUS | _03_RTC_AUTO_ADJUSTMENT_VALUE;
    while (( _40_RTC_TIMER_ERROR_ADJUST_PLUS | _03_RTC_AUTO_ADJUSTMENT_VALUE) != RTC.RADJ.BYTE)
    {
        /* Wait for this write to complete. */
    }
    ...
}

```

## 1.6 Schedule for Fixing the Problem

This problem will be fixed in the following product versions. (Scheduled to be released in January 2020.)

- e<sup>2</sup> studio V7.7.0
- Smart Configurator for RX V2.4.0

Revision History

Rev.	Date	Description	
		Page	Summary
1.00	Sep.16.19	-	First edition issued

Renesas Electronics has used reasonable care in preparing the information included in this document, but Renesas Electronics does not warrant that such information is error free. Renesas Electronics assumes no liability whatsoever for any damages incurred by you resulting from errors in or omissions from the information included herein.

The past news contents have been based on information at the time of publication. Now changed or invalid information may be included.

URLs in Tool News also may be subject to change or become invalid without prior notice.

Corporate Headquarters

TOYOSU FORESIA, 3-2-24 Toyosu, Koto-ku, Tokyo 135-0061 Japan  
[www.renesas.com](http://www.renesas.com)

Contact information

For further information on a product, technology, the most up-to-date version of a document, or your nearest sales office, please visit:  
[www.renesas.com/contact/](http://www.renesas.com/contact/)

Trademarks

Renesas and the Renesas logo are trademarks of Renesas Electronics Corporation. All trademarks and registered trademarks are the property of their respective owners.