RENESAS 24MHz 3.2 x 2.5mm Reference Crystal


603-24-127

DATASHEET


Specifications

Parameters	Ratings/Units	
Frequency	24.000 MHz	
Resonance Mode	Fundamental	
Frequency Tolerance @ 25°C	±30 PPM Max	
Frequency Stability, ref @ 25°C Over Operating Temperature Range	±30 PPM Max	
Temperature Range, Operating (TOPR)	-40°C ~ +85°C	
Temperature Range, Storage (TSTG)	-40°C ~ +85°C	
Equivalent Series Resistance (ESR)	90 Ohms Max	
Shunt Capacitance (Co)	7 pF Max	
Load Capacitance (CL)	12 pF	
Drive Level	0.1 mW Max	
Aging	±5 PPM/Yr Max	
Maximum Soldering Temp / Time	260°C / 10 Seconds	
Moisture Sensitivity Level (MSL)	1	
Termination Finish:	Au	
Weight (TYP)	16.75 mg	
RoHS Compliant, Pb-free		

Package Outline and Dimensions (JA4)



RENESAS



Ordering Information

Part / Order Number	Shipping Packaging	Package	Temperature
603-24-127JA4I	Cut-Tape	3.2 x 2.5 x 1.0 mm JA4 CLCC	-40 to +85 °C
603-24-127JA4I8	Tape and Reel	3.2 x 2.5 x 1.0 mm JA4 CLCC	-40 to +85 °C

IMPORTANT NOTICE AND DISCLAIMER

RENESAS ELECTRONICS CORPORATION AND ITS SUBSIDIARIES ("RENESAS") PROVIDES TECHNICAL SPECIFICATIONS AND RELIABILITY DATA (INCLUDING DATASHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS OR IMPLIED, INCLUDING, WITHOUT LIMITATION, ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, OR NON-INFRINGEMENT OF THIRD-PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for developers who are designing with Renesas products. You are solely responsible for (1) selecting the appropriate products for your application, (2) designing, validating, and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, or other requirements. These resources are subject to change without notice. Renesas grants you permission to use these resources only to develop an application that uses Renesas products. Other reproduction or use of these resources is strictly prohibited. No license is granted to any other Renesas intellectual property or to any third-party intellectual property. Renesas disclaims responsibility for, and you will fully indemnify Renesas and its representatives against, any claims, damages, costs, losses, or liabilities arising from your use of these resources. Renesas' products are provided only subject to Renesas' Terms and Conditions of Sale or other applicable terms agreed to in writing. No use of any Renesas resources expands or otherwise alters any applicable warranties or warranty disclaimers for these products.

(Disclaimer Rev.1.01)

Corporate Headquarters

TOYOSU FORESIA, 3-2-24 Toyosu, Koto-ku, Tokyo 135-0061, Japan www.renesas.com

Trademarks

Renesas and the Renesas logo are trademarks of Renesas Electronics Corporation. All trademarks and registered trademarks are the property of their respective owners.

Contact Information

For further information on a product, technology, the most up-to-date version of a document, or your nearest sales office, please visit <u>www.renesas.com/contact-us/</u>.